MDB-RS232 测试 PAX30 刷卡器注意事项

这个设备，在测试的时候需要使用以下三条指令：
（以下仅作示例，用户根据协议可以做修改）
110002000002　　（配置参数）
1101FFFF0000　　（设置最大最小价格）
17004E4543303030303030303030303020202020204B5245412020200005　（读取 ID）
以上三条指令发送后，设备都会做出回复，必须要收到回复后发送下一个指令
然后发送：
1401　　（使能指令）

这个时候，就可以屏幕上点“start”去开始测试交易了。
然后串口发送：
1300000A0001　　就会看到屏幕上有价格了，按照协议和提示继续后续的测试就可以了

MDB-RS232 with POS PAX30 card reader

This PAX30 device requires the following three commands to start the test:
(Below is only an example, users can make modifications according to the protocol)
1100020000002　　(configuration parameters)
1101FFF0000　　(set maximum and minimum prices)
17004E4543303030303030030303030030302020202020204B52454120200005 (Read ID)
After the above three commands are sent, the device will respond and must receive the response before sending the next command
Then we send:
1401　　(enable command)

And now, you can click "start" on the screen to start the Vend session
After receive the Vend start data, Then We can sends:
1300000A0001
Then will see the price on the screen.
Follow the protocol and prompts to continue with subsequent testing